ECOLOR 250 XT- DMX PROTOCOL 8bit

Channel	Value	Function	Type of control
1		**Cyan**	
	0-255	Cyan from 0 (white) to 255 (full cyan)	proportional
2		**Magenta**	
	0-255	Magenta from 0 (white) to 255 (full magenta)	proportional
3		**Yellow**	
	0-255	Yellow from 0 (white) to 255 (full yellow)	proportional
4		**Dimmer intensity**	
	0-255	Intensity from 0 to 100%	proportional
5		**Speed of CMY and dimmer**	
	0-255	From max. speed to min. speed	proportional
6		**Colour macros,Lamp On/Off,Reset**	
	0-7	Off	step
	8-15	Macro 1	step
	16-23	Macro 2	step
	24-31	Macro 3	step
	32-39	Macro 4	step
	40-47	Macro 5	step
	48-55	Macro 6	step
	56-63	Macro 7	step
	64-71	Macro 8	step
	72-79	Macro 9	step
	80-87	Macro 10	step
	88-95	Macro 11	step
	96-103	Macro 12	step
	104-111	Macro 13	step
	112-119	Macro 14	step
	120-127	Macro 15	step
	128-139	Lamp On after 3 sec.,reset	step
	140-229	No function	step
	230-239	Lamp Off after 3 sec	step
	240-255	No function	step